

## **Modification procedure from FM only into AM/FM**

Albrecht 40 CH FM CB radios AE 5080 FM and AE 5280 FM, which have already a function key (F") key instead of the conventional AM/FM switch on the front panel, can be easily converted to AM/FM by soldering jumpers on the front panel PCB.

Procedure AE 5280 and 5080 FM versions:

Open loudspeaker side of cabinet.

### **AE 5080 FM:**

On the soldering side of the front panel board You will find solder jumper fields, named A/F, CH 19, 24, 25, and 26. These points are located just besides the volume switch and easy to find.

delete the solder connection across the CH 19 field and solder a new connection across the A/F field. This will change the Function key from CH 19 into A/F, and then the front panel key F works again as AM/FM switch.

### **AE 5280 FM:**

You will find soldering jumper fields A/F, CH 19, ME, CH9 just between CPU and the lower edge of the front panel board. These jumpers can modify the keys "F" and " MEMO".

For AM/FM, delete the solder bridge at the CH 19 field and solder a new bridge across the A/F field.

It is not possible to modify the output power in AM mode from 1 Watts to 4 Watts, because both models have no transformer for AM Modulation.

These modifications are only legal in countries which allow AM and FM on 40 Channels and where a valid approval has been obtained. In any case, the present approval sticker of the FM CEPT version must be replaced by the appropriate approval sticker for this country.

Albrecht Electronic GmbH