

ICOM IC-E90 TX Power after Expand

TX Power measured with original Battery Pack. It is possible, that other IC-E90 will be a little different, but you can see the typical TX Output between the band edges. **Please note:** **The Display will always show max. Power Output! But this is not true!** TX only in FM!

MHz	TX Output in Watt
45,5	3,2
52	4,6
70	3,5
80	0,1
83	0,01
End of 6m	
91,5 MHz	0,5
110	0,4
120	0,9
130	2,4
140	3,3
145	4
150	3,5
160	0,9
170	0,4
180	0,2
200	0,23
210	0,11
220	0,06
224	0,02
End of 2m	
300 MHz	0,25
320	0,35
350	0,65
390	0,65
400	3,2
430	3,8
446	3,2
460	2,9
500	1,5
510	1,1
530	0,4
540	0,25
550	0,15
570	0,09
580	0,08
600	OFF